


2 in 1 Soldering & Desoldering Station

Model : **ZD-917**

Including the spare parts below :



FEATURES

- ◆ Complete solder /desolder station for production and service use.
- ◆ The soldering iron and desoldering gun can be operated independently or together.
- ◆ Temperature is micro-processor controlled and can be adjusted from 160 °C to 480 °C.

- ◆ The control unit has two LCDs that display the set temperature and the actual temperature in °C and °F.
- ◆ The heating element is made of PTC.
- ◆ The temperature can be easily adjusted by simple up/down buttons.

Specifications

Code	Voltage	Note
89-1711	110-130V	ESD
89-1712	220-240V	
89-1713	110-130V	
89-1714	220-240V	

Spare heater

Code	Voltage	Power	Use for	Note
78-415B	24V	60W	88-415A/B	with temperature probe
78-551B	24V	80W	88-552A/B	




Spare tips

Code	Model
79-1516	TIP N5-1
79-1526	TIP N5-2
79-1536	TIP N5-3

Spare Filter for:
ZD-915 ZD-917
ZD-985 ZD-987
Φ16.8 Code:79-5518
Φ20.8 Code:79-5519



TIPS : (N5)



Desoldering Gun
Clearing Tool for:
ZD-552
Code:79-5511
79-5512
79-5513

Φ0.7 Φ0.9 Φ0.12

Spare soldering iron

Code	Voltage	Power	Note
88-415A	24V	60W	with temperature probe



with 4 pins



Spare tips

Code	Model	Note
79-1416	TIP N4-1	High quality
79-1426	TIP N4-2	
79-1436	TIP N4-3	
79-1446	TIP N4-4	

Spare desoldering gun

Code	Voltage	Power	Note
88-552A	24V	80W	with temperature probe



with 6 pins



Sponge

Code	Size
79-7305	65x50mm



Model	Package	Q'ty/ctn	Carton Size	N.W	G.W
ZD-917	Gift box	1set	36x29x23cm	6kgs	7kgs